

DC SOLID STATE RELAY

IO-X-0604D COM (+)
COM (-)

IO SERIES





SPECIFICATIONS

MODEL NO.	CONTROL VOLTAGE RANGE	MUST TURN OFF VOLTAGE	INPUT IMPEDANCE	MAX LOAD CURRENT	LOAD VOLTAGE RANGE	MIN BLOCKING VOLTAGE	MAX OFF-STATE LEAKAGE	FREQUENCY RANGE	MAX 1-CYCLE PEAK SURGE
IO-2-0604D	3 TO 32 VDC	MAX1.0 VDC	1.5Kohm	4A	3~32VDC	60VDC	LESS 1 mA	47~70HZ	8.5A
MODEL NO.	MAX OFF STATE dv/dt	MAX ON-STATE VOLTAGE DROP	ISOLATE IMPEDENCE	DIELECTRIC STRENGTH INPUT-OUTPUT	DIELECTRIC STRENGTH INPUT-OUTPUT-CASE	TURN ON TIME	TURN OFF TIME	CAPACITANCE IN-OUT	WEIGHT (g)
IO-2-0604D	200 V/μ SEC	1.2Vrms	10 ⁹ ohm	2500Vrms	—	LESS 2mSec	LESS1/2cycle	LESS15pf	12 g


PS:X= 2PORT.4PORT.8PORT

OUTLINE DIMENSIONS (unit:mm)





Model	Dimension (LxWxH)mm
IO-2-0604D	34x85x51
IO-4-0604D	64x85x51
IO-8-0604D	124x85x51



EQUIVALENT CIRCUIT



CHARACTERISTIC CURVES



勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
[Http://www.100y.com.tw](http://www.100y.com.tw)

DC SOLID STATE RELAY

KF0602D
KF0604D

KF SERIES




勝特力材料 886-3-5753170
勝特力电子(上海) 86-21-54151736
勝特力电子(深圳) 86-755-83298787
Http://www.100y.com.tw


SPECIFICATIONS

MODEL NO.	CONTROL VOLTAGE RANGE	MUST TURN OFF VOLTAGE	INPUT IMPEDANCE	MAX LOAD CURRENT	LOAD VOLTAGE RANGE	MIN LATCHING VOLTAGE	MAX OFF STATE LEAKAGE	FREQUENCY RANGE	MAX 1-CYCLE PEAK SURGE
KF0602D	3 TO 32 VDC	MAX1.0 VDC	1.5Kohm	2A	3~60VDC	80VDC	LESS 1 mA	47~70HZ	3A
KF0604D	3 TO 32 VDC	MAX1.0 VDC	1.5Kohm	4A	3~60VDC	80VDC	LESS 1 mA	47~70HZ	8.5A
MODEL NO.	MAX OFF STATE dI/dt	MAX ON STATE VOLTAGE DROP	ISOLATE IMPEDANCE	DIELECTRIC STRENGTH INPUT-OUTPUT	DIELECTRIC STRENGTH INPUT-OUTPUT CASE	TURN ON TIME	TURN OFF TIME	CAPACITANCE IN-OUT	WEIGHT (g)
KF0602D	200 V/ μ SEC	1.2Vrms	10^9 ohm	2500Vrms	—	LESS 2mSec	LESS1/2cycle	LESS15pf	10 g
KF0604D	200 V/ μ SEC	1.2Vrms	10^9 ohm	2500Vrms	—	LESS 2mSec	LESS1/2cycle	LESS15pf	12 g

OUTLINE DIMENSIONS (unit:mm)



EQUIVALENT CIRCUIT



- 1.INPUT CIRCUIT
- 2.PHOTO DETECTOR
- 3.AMPLIFIER
- 4.PROTECTED CIRCUIT

CHARACTERISTIC CURVES

